

Image Pickup Apparatus

BACKGROUND OF THE INVENTION

Field of the Invention

5 The present invention relates to a solid-state image pickup element for obtaining an image signal and an image pickup apparatus using the same and, more particularly, to a CMOS compatible XY address amplifier type solid-state image pickup element and an image pickup apparatus using the same.

Related Background Art

10 Conventional solid-state image pickup elements have a MOS structure made up of a conductor such as a metal capable of performing photoelectric conversion, an insulator such as an oxide, and a semiconductor, and are classified into an FET type and CCD type depending on the photocarrier moving method. Solid-state image pickup elements are used in various fields including a solar battery, image camera, copying machine, and facsimile apparatus, and are technically being increased in conversion efficiency and integration density. One of such solid-state image pickup elements is a CMOS process compatible sensor (to be referred to as a CMOS sensor hereinafter). Sensors of this type are proposed in documents, e.g., IEEE Transactions on Electron Device Vol. 41, pp. 452 - 453, 1994. Another CMOS sensor is disclosed in Japanese Laid-Open Patent

Application No. 9-46596 in which the sensor is suitable for downsizing of pixels and addition/non-addition of a pixel signal can be arbitrarily switched.

5 In the prior art, downsizing cannot be effectively achieved unless the pitch of a vertical scanning circuit is also decreased along with pixel reduction.

Further, a scanning circuit for efficiently performing addition/non-addition switching operation has not satisfactorily been examined.

10

SUMMARY OF THE INVENTION

It is an object of the present invention to provide a solid-state image pickup element much smaller than a conventional solid-state image pickup element.

15

To achieve the above object, according to an aspect of the present invention, there is provided a solid-state image pickup element comprising a plurality of pixel blocks each having a plurality of photoelectric conversion elements, a plurality of transfer switches for transferring signals from the respective photoelectric conversion elements, and a common amplifier for receiving signals from the plurality of transfer switches, and a scanning circuit for outputting a scanning clock for each pixel block.

20

25

In this arrangement, the circuit scale of the scanning circuit can be reduced, resulting in a small area of the solid-state image pickup element.

The above and other objects and features of the present invention will be apparent from the following description in conjunction with the accompanying drawings.

5

BRIEF DESCRIPTION OF THE DRAWINGS

Fig. 1 is a circuit diagram for explaining the first embodiment of the present invention;

10 Fig. 2 is a sectional view showing a pixel according to the first embodiment of the present invention;

Fig. 3 is a first timing chart according to the first embodiment of the present invention;

15 Fig. 4 is a second timing chart according to the first embodiment of the present invention;

Fig. 5 is a circuit diagram for explaining the second embodiment of the present invention;

Fig. 6 is a circuit diagram for explaining the third embodiment of the present invention;

20 Fig. 7 is a circuit diagram for explaining the fourth embodiment of the present invention;

Fig. 8 is a circuit diagram showing a decoder circuit;

25 Fig. 9 is a timing chart showing the operation of the decoder circuit;

Fig. 10 is a schematic block diagram showing an image pickup system according to the present invention;

Fig. 11 is a circuit diagram showing an arrangement when an arithmetic processing unit is constituted by OR and NOR gates; and

Fig. 12 is a timing chart showing the operation of the arrangement in Fig. 11.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

Preferred embodiments of the present invention will be described in detail below with reference to the accompanying drawings.

Fig. 1 is a circuit diagram showing the equivalent circuit of a solid-state image pickup element according to the first embodiment of the present invention. In Fig. 1, reference numerals 1-1 and 1-2 denote photoelectric conversion elements such as photodiodes; 5-1 and 5-2, transfer switch MOS transistors; 4, a reset MOS transistor; 2, an input MOS transistor of a source follower amplifier; 3, a vertical selection MOS transistor; 7, a source follower load transistor; 8, a dark output transfer MOS transistor; 9, a bright output transfer transistor; 10, a dark output accumulation capacitor; 11, a bright output accumulation capacitor; 12-1 and 12-2, horizontal transfer MOS transistors for transferring dark and bright outputs, respectively; 13-1 and 13-2, horizontal output line reset MOS transistors; 14, a differential output amplifier; 15, a horizontal scanning circuit; 16, vertical scanning

circuits arranged for respective pixel blocks; and 17, an arithmetic operation processing unit constituted by AND and NAND gates in the first embodiment.

Fig. 2 is a sectional view of a pixel. In Fig. 2, reference numeral 201 denotes a p-type well; 202, a gate oxide layer; 203-1 and 203-2, gate electrodes of transfer MOS transistors formed from poly-Si or the like; 204, an n⁺-type FD (Floating Diffusion) portion serving as a signal input portion; 205-1 and 205-2, photoelectric conversion portions. The FD portion 204 is connected to the two photoelectric conversion portions 205-1 and 205-2 via the transfer MOS transistors 5-1 and 5-2. In Fig. 2, the drains of the two transfer MOS transistors 5-1 and 5-2 and the FD portion 204 are shared by each other, thus increasing the sensitivity by micropatterning and reduction in the capacitance of the FD portion 204. Alternatively, the two transfer MOS transistors 5-1 and 5-2 may have their own drains which are connected by a metal line to form an FD portion.

The operation will be described briefly with reference to the timing chart of Fig. 3. In Fig. 3, V1 and V2 represent vertical scanning timing clocks sequentially output from the vertical scanning circuit 16; ϕ RES, an external reset clock input to the arithmetic processing unit 17; ϕ SEL, an external vertical selection clock input to the arithmetic

processing unit 17; and $\phi TX1$ and $\phi TX2$, first and second external transfer clocks input to the arithmetic processing unit 17.

5 The photoelectric conversion element 1 is reset by turning on the transfer switch 5 and reset switch 4. After the transfer switch 5 is turned off, accumulation operation starts. At the end of the accumulation time, AND operation of ϕSEL and the timing clock V1 from the vertical scanning circuit 16 are performed, so that a
10 vertical selection clock $\phi sel1$ goes high at time T0, and then the vertical selection MOS transistor 3 is turned on to operate source follower amplifiers corresponding to the pixels on the first and second lines. Similarly, NAND operation of ϕRES and the
15 timing clock V1 from the vertical scanning circuit 16 are performed, so that a reset clock $\phi res1$ goes low, and then the reset of the FD portion 204 is stopped, so that the FD portion 204 is floated. At time T1, a clock ϕTN goes high, and the dark voltage of the FD
20 portion 204 is output to the accumulation capacitor C_{TN} 10 by source follower operation.

To output photoelectrical conversion outputs from the pixels on the first line, AND operation of $\phi TX1$ and the timing clock V1 from the vertical scanning circuit
25 16 are performed at time T2, so that a transfer clock $\phi tx11$ goes high to turn on the transfer MOS transistor 5, and then signal charges are transferred

to the FD portion 204. With this receiving of the charges, the potential of the FD portion 204 appears to change depending on light. At time T3, a clock ϕ_{TS} goes high, and the voltage of the FD portion 204 is
5 output to the accumulation capacitor C_{TS} 11 by source follower operation. At this time, dark and bright outputs from the pixels on the first line are respectively accumulated in the accumulation capacitors C_{TN} 10 and C_{TS} 11. At time T4, a horizontal output line
10 reset clock ϕ_{HC} temporarily goes high to reset the horizontal output line. The dark and bright outputs from the pixels are output in response to a scanning timing signal from the horizontal scanning circuit 15 during the horizontal transfer period. Then, the
15 differential output amplifier 14 obtains a differential output V_{out} between the two outputs, thereby outputting a signal having a high S/N ratio from which random noise and fixed pattern noise of pixels are removed.

The operation can be easily switched to signal
20 read-out of the second line by clock operation using the transfer clock ϕ_{TX2} instead of the external transfer clock ϕ_{TX1} at the same timing in the above-described read sequence.

The first embodiment realizes sensor read
25 operation by generating a vertical scanning timing signal only once while controlling the pixel arrays of the two, first and second lines. Thus, the circuit

arrangement of the vertical scanning circuit can be simplified, the vertical scanning circuit can be reduced along with pixel reduction, and a small-size solid-state image pickup element can be implemented.

5 In the first embodiment, a pair of circuits for generating the reset clock ϕ_{res} and vertical selection clock ϕ_{sel} necessary for read of each of the first and second lines are arranged for and shared by the two, first and second lines, thereby also reducing the
10 circuit scale.

 Addition and read-out of signals from two pixels at the FD portion 204 can also be realized by changing only the timings of application pulses without changing the circuit arrangement of the first embodiment.

15 Fig. 4 is a timing chart when signals from two, upper and lower pixels are added. The timings of the transfer clocks ϕ_{tx11} and ϕ_{tx12} are shifted to each other by one line in Fig. 3 showing the non-addition mode, whereas their timings are the same in the
20 addition mode. More specifically, to simultaneously read out signals from the photoelectric conversion elements 1-1 and 1-2, the clock ϕ_{TN} goes high to read out a noise component from a vertical output line. Then, the transfer clocks ϕ_{tx11} and ϕ_{tx12}
25 simultaneously go high and low respectively, to transfer signals to the FD portion 204. Accordingly, the signals from the two, upper and lower photoelectric

conversion elements 1 can be added by the FD portion 204 at the same timing.

The first embodiment can easily implement addition function by only changing the timings of the external transfer clocks $\phi TX1$ and $\phi TX2$.

The arithmetic processing unit 17 in the first embodiment is made up of AND and NAND gates, but is not limited to this.

Fig. 11 shows an arrangement of the first embodiment when the arithmetic processing unit is made up of OR and NOR gates. Fig. 12 is a timing chart showing the operation in this arrangement. This arrangement can also generate a desired clock by processing the vertical scanning timing clock and the clocks ϕRES , ϕSEL , $\phi TX1$, and $\phi TX2$ by the arithmetic processing unit. In the pixel layout represented by this arrangement, the number of transistors which constitute gates can be more reduced when the arithmetic processing unit is made up of OR and NOR gates than when it is made up of AND and NAND gates. This can further reduce the circuit scale.

Fig. 5 is a circuit diagram showing the equivalent circuit of a solid-state image pickup element according to the second embodiment of the present invention. In the second embodiment, four pixels in the Y direction form one pixel block, and one vertical scanning circuit 16 is arranged for every four pixels.

In the second embodiment, sensor read operation can be performed by generating a vertical scanning timing signal only once while controlling the pixel arrays of the four, first to fourth lines. The circuit arrangement of the vertical scanning circuit can be more simplified than in the first embodiment. The scanning circuit can be reduced along with pixel reduction to implement a smaller-size solid-state image pickup element.

10 A pair of circuits for generating a reset clock ϕ_{res} and vertical selection clock ϕ_{sel} are arranged for and shared by the four, first to fourth lines, thereby also reducing the circuit scale.

15 Addition and read-out of signals from four pixels in the Y direction at an FD portion 204 can also be easily realized by changing only the timings of application pulses without changing the circuit arrangement of the second embodiment.

20 Fig. 6 is a circuit diagram showing the equivalent circuit of a solid-state image pickup element according to the third embodiment of the present invention. In the third embodiment, an arithmetic processing unit 17 is comprised of transfer gates 601 and switch MOS transistors 602. Reference numeral 603 denotes an inverter which generates the inverted signal of a
25 vertical scanning timing clock.

The operation of the third embodiment will be explained with reference to the timing chart of Fig. 3. Similar to the first embodiment, after photoelectric conversion elements are reset, accumulation operation starts. At the end of the accumulation time, a timing output V1 from a vertical scanning circuit 16 goes high to turn on transfer gates 601-1 to 601-4. External clocks ϕ SEL, ϕ RES, ϕ TX1, and ϕ TX2 are transferred to pixels via the transfer gates 601-1 to 601-4, and act as clocks which operate respective pixels at the same timings as those described in the first embodiment. After signals on the first and second lines are read out, the vertical scanning timing clock V1 goes low to turn on the switch MOS transistors 602, and the gates of vertical selection MOS transistors 3 and those of transfer MOS transistors 5 corresponding to the first and second lines are fixed to a turn-off potential. The gates of reset MOS transistors 4 are fixed to a turn-on potential.

The third embodiment also attains the same effects as those of the first and second embodiments. In addition, the third embodiment can reduce the circuit scale of the arithmetic processing unit 17 much more than the first and second embodiments. In the third embodiment, an external clock is directly transferred to the gate of a pixel transistor via the transfer gate 601. In the first and second embodiments, the clock

amplitude is uniquely determined by the power supply voltage of a logic gate. In the third embodiment, the clock amplitude can be freely changed by changing the amplitude of an input external clock. For example, the gate voltage when the transfer MOS transistor is OFF is set slightly higher than the threshold voltage of the MOS during the accumulation period. This setting enables lateral overflow draining of discharging to a power source VDD, through the transfer MOS transistor and reset MOS transistor, excessive charges generated when strong light is incident on a photoelectric conversion element 1.

Fig. 7 is a circuit diagram showing the equivalent circuit of a solid-state image pickup element according to the fourth embodiment of the present invention. In the fourth embodiment, a decoder circuit 701 is arranged between an external clock input portion and an arithmetic processing unit to reduce the number of externally input clocks.

Fig. 8 is a circuit diagram showing the decoder circuit, and Fig. 9 is a timing chart showing its operation. As shown in Fig. 9, an external clock ϕ_{TX} is distributed to any one of ϕ_{TX1} to ϕ_{TX4} in accordance with whether decoder clocks ϕ_{DEC1} and ϕ_{DEC2} are high or low, thereby outputting the selected clock. The output clocks ϕ_{TX1} to ϕ_{TX4} and vertical scanning timing clocks are ANDed to generate transfer clocks.

Compared to the second embodiment, the fourth embodiment can reduce the number of external clocks by one by arranging the decoder circuit 701. In the fourth embodiment, four pixels in the Y direction form one pixel block. For example, when eight pixels form one pixel block, the second embodiment requires eight external transfer clocks, but the fourth embodiment can realize an operation similar to the above-described one by a total of four clocks, i.e., one external transfer clock and three decoder clocks.

The fourth embodiment can, therefore, obtain new effects: the number of external clocks can be reduced, the solid-state image pickup element can be easily controlled, and the area for laying out clock wires can be reduced.

The vertical scanning circuit in each of the first to fourth embodiments may be a shift register circuit or decoder circuit. The shift register circuit can reduce the circuit scale more than the decoder circuit. The decoder circuit can freely select the pixel column selection order and can realize various signal read-out orders in comparison with the shift register circuit.

As has been described above, the first to fourth embodiments can implement a solid-state image pickup element in which the peripheral circuit is downsized, resulting in low cost by downsizing and high yield, a

small-size package, a small-size optical system, and a simple external control circuit.

Fig. 10 is a schematic view showing an image pickup apparatus such as a digital camera. As shown in Fig. 10, image light passing through an optical system 71 and iris 80 forms an image on a CMOS sensor 72. The optical information is converted into an electrical signal by a pixel array arranged on the CMOS sensor 72. Noise is removed from the electrical signal, and the resultant signal is output. The output signal undergoes signal conversion processing by a signal processing circuit 73 by a predetermined method, and output. The processed signal is recorded by an information recording device or transferred via a recording and communication system 74. The recorded or transferred signal is reproduced by a reproducing system 77. The iris 80, CMOS sensor 72, and signal processing circuit 73 are controlled by a timing control circuit 75, whereas the optical system 71, timing control circuit 75, recording and communication system 74, and reproducing system 77 are controlled by a system control circuit 76. In this case, the CMOS sensor 72 is a solid-state image pickup element described in each of the first to fourth embodiments.

Many widely different embodiments of the present invention may be constructed without departing from the spirit and scope of the present invention. It should

be understood that the present invention is not limited to the specific embodiments described in the specification, except as defined in the appended claims.

10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
2212
2213
2214
2215
2216
2217
2218
2219
2220
2221
2222
2223
2224
2225
2226
2227
2228
2229
2230
2231
2232
2233